

microlab® 麦博

x13 2.1 powerful high fidelity subwoofer speaker system for multimedia and music entertainment

Features:

- Powerful 2.1 subwoofer speaker system for surround effects and acoustics
- Satellites can be floor standing (detachable), or on the desk, or mounted on the wall
- Full range clear acoustic with deep powerful bass
- Designed using many proven technologies such as Finecone V12, FINE BOX, FINE CONE, and FINE MOTO
- Comes with wireless infrared remote control



Specifications:

Amplifier

- Output power: 68 Watt RMS
- Power distribution: 14 Watt x 2 + 40 Watt
- Harmonic distortion: < 0.3% 1 W 1 kHz
- Frequency response: 30 Hz - 20 kHz
- Signal/Noise ratio: > 75 dB
- Separation: > 48 dB
- Input sensitivity: 400 mV
- Nominal impedance: 4 ohm

Speakers

- Tweeter driver type: 2" x 2
- Tweeter rated power: 14 Watt x 2
- Bass driver type: 6.5"
- Bass rated power: 40 Watt
- Frequency range: 30 Hz - 20 kHz

Interfaces

- Output: 2RCA
- Input: 3.5 mm stereo, 2RCA

Power

- Power supply: AC 220 V - 240 V, 50 Hz 450 mA
- Fuse: T630mAL250V

Package contents

- x13 subwoofer
- x13 satellites x 2
- Audio cable
- Interconnect speaker cables x 2
- Wireless remote control
- User manual

Dimension

- Subwoofer dimension: 220 x 327 x 312 mm (W x H x D)
- Satellites dimension: 90 x 193 x 102 mm
- Product net weight: 8.0 kg
- Giftbox dimension: 360 x 279 x 444 mm
- Giftbox gross weight: 8.7 kg
- Export carton dimension: 574 x 372 x 462 mm
- Export carton gross weight: 18.4 kg

Warranty Notice: *1 Year Warranty

Microlab Electronics Company Limited

Baozi South Road, Microlab Industrial Park, Shenzhen Grand Industrial Zone, Longgang District, Shenzhen, China 518122
Tel: +86 75528291111 Fax: +86 75528290000
Email: jennifersheng@microlab.cn

EAN: 694519885009 6

Ver: 1.5



Product image, Terms and Specifications are subject to changes without further notice

© 2011 Microlab Electronics Co., Ltd