

# microlab

## just listen

### M-300(11) Clear and powerful 2.1 subwoofer speaker system

#### Features:

- Quality 2.1 speaker system with built-in amplifier
- Satellite speakers with metal diamond texture
- Front panel volume controls
- Full audio spectrum performances, ideal for your favourite entertainment from Mp3, Mp4, CD/DVD movies and digital playbacks
- Specially designed woofer for bass and resolution
- Comes with 3.5mm stereo connection that connects to most media players and computers



#### Specifications:

##### Amplifier

- Output power: 40 Watt
- Distribution: 10 Watt x 2 + 20 Watt RMS
- Harmonic distortion: < 0.3% 1 Watt 1kHz
- Frequency range: 30 Hz - 20 kHz
- Signal/Noise ratio: > 75 dB
- Separation: > 45 dB
- Input sensitivity: 400 mV

##### Speakers

- Tweeter drive unit: 2.5" x 2
- Rated power: 10 Watt 6 ohm
- Woofer drive unit: 5"
- Rated power: 30 Watt 8 ohm

##### Interfaces

- Input: 3.5mm stereo jack
- Output: 2RCA

##### Power

- Power supply: AC 100 V - 220 V ~ 50 / 60 Hz  
360 mA

##### Package contents

- |                               |       |
|-------------------------------|-------|
| • M-300(11) subwoofer         | 1 pc  |
| • M-300(11) satellites        | 2 pcs |
| • 3.5mm to 3.5mm stereo cable | 1 pc  |
| • User manual                 | 1 pc  |

##### Dimensions

- Subwoofer: 165 (L) x 212 (H) x 313 (D) mm
- Satellites: 80 (L) x 178 (H) x 83 (D) mm
- Product net weight: 3.2 kg
- Giftbox dimension: 357 (L) x 240 (W) x 326 (H)mm
- Giftbox gross weight: 3.9 kg
- Export carton dimension: 494 (L) x 371 (W) x 668 (H)mm
- Export carton gross weight: 16.6 kg

**Warranty Notice:** \*1 Year Warranty

#### Microlab Electronics Company Limited

Baozi South Road, Shenzhen Microlab Industrial Park,  
Shenzhen Grand Industrial Zone, PingShan New District,  
Shenzhen, China 518122

Tel: +86 75528291111 Fax: +86 75528290000

Email: jennifersheng@microlab.cn

EAN: 694519885210 6

Ver: 1.0



Product image, Terms and Specifications are subject to changes without further notice

© 2011 Microlab Electronics Co., Ltd